

E-BACNET-V and E-BACNET2-V upgrade procedure

- 1 Power off the unit by removing the power cord.
- 2 Remove the cover by unscrewing the two screws at the sides (see photo below).
- 3 If there is a SD card already present: Eject the SD card at the right side by pressing and then release it. Mail back to Regin AB.
- 4 Insert the new SD card labeled "E-BACNET2-V 2.0-1-08" or later and firmly press it and release pressure once you hear a 'click'.
- 5 Reattach the power cord and power up the E-BACNET2-V.
- 6 The unit will beep once right after the power is turned on. The upgrade procedure is started.
- 7 Wait between 30 and 60 seconds and the unit will beep again. The upgrade procedure is finished. The unit is now an upgraded E-BACNET2-V unit.
- 8 Some 20 seconds after the beep the Ready-LED will be lit and the S0 TX and RX LEDs will flash if the communication to the Corrigo is working. If no Corrigo is attached, only the S0 TX led is flashing (about 1Hz)
- 9 Power off the E-BACNET-V by removing the power cord.
- 10 Eject the SD card.
- 11 Replace the cover.

The E-BACNET2-V now has factory default IP settings, but any user configuration like BACnet device id, location etc. is left unchanged. Run the E-BACNET2 configuration software to change IP settings and to verify the firmware version.

